



BNL-98877-2013-CP

***Multi-slit based emittance measurement study
for BNL ERL***

C. Liu, D. Gassner, D. Kayran, M. Minty, P. Thieberger

*Presented at the 4th International Particle Accelerator Conference (IPAC 13)
Shanghai, China
May 12-17, 2013*

**Collider-Accelerator Department
Brookhaven National Laboratory**

**U.S. Department of Energy
DOE Office of Science**

Notice: This manuscript has been authored by employees of Brookhaven Science Associates, LLC under Contract No. DE-AC02-98CH10886 with the U.S. Department of Energy. The publisher by accepting the manuscript for publication acknowledges that the United States Government retains a non-exclusive, paid-up, irrevocable, world-wide license to publish or reproduce the published form of this manuscript, or allow others to do so, for United States Government purposes.

This preprint is intended for publication in a journal or proceedings. Since changes may be made before publication, it may not be cited or reproduced without the author's permission.

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, nor any of their contractors, subcontractors, or their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or any third party's use or the results of such use of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof or its contractors or subcontractors. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

Multi-slit Based Emittance Measurement Study for BNL ERL*

C. Liu[†], D. Gassner, D. Kayran, M. Minty, P. Thieberger, BNL, Upton, NY 11973, USA

Abstract

A code for determining the beam emittance from a multi-slit image has been developed. To verify its validity, we simulated a beam distribution in 4D phase space at the multi-slit position and the resulting image at a downstream profile measurement device. We applied the algorithm to this image pattern to recover the beam emittance at the slit position. The dependence of the relative difference of the inferred emittance and the input emittance on the slit width and drift length are studied in detail and presented in this report.

INTRODUCTION

At the BNL ERL, a multi-slit device will be used for direct measurement of two dimensional beam phase space, which samples particles at discrete horizontal (or vertical) positions and projects the sampled beam on a downstream screen. The beam size and divergence of the sampled beam can be determined using the image acquired by the downstream profile device and the mask pattern dimensions. The emittance of the beamlets sampled by the multi-slit mask will be shown to be representative of the emittance of the beam incident on the mask. Here we will present the algorithm and its application using simulated data, and a study of geometry-dependent systematic errors in the inferred emittance.

ALGORITHM

The schematic for a multi-slit emittance measurement device is shown in Fig. 1. The incoming beam is sampled by a multi-slit mask. Beamlets formed by the mask project onto a profile measurement device and the resulting image is recorded. The beam size at the slits can be determined by the dimension of the slit pattern and the intensity of the beamlets. The beam divergence can be determined by the intensity distribution on the profiler.

The well accepted rules for multi-slit mask design [1, 2] are: the slit spacing is chosen such that beam is divided to 4-8 beamlets; the slit width is as narrow as possible as limited by current fabrication techniques; the drift length between mask and profiler is such that beamlets will spread out on the profiler until they overlapping; the mask thickness is thick enough to stop most incoming particles; and the opening angle of the slit is comparable to the anticipated beam divergence.

Detailed formulas for slits emittance measurement can be found in Ref. [3]. The projection of the recorded im-




Figure 1: Schematic of a multi-slit emittance measurement device (not to scale)

age is usually treated as a multi-Gaussian distribution. The average divergence of each beamlet is calculated based on slit positions and peak positions. The rms divergence of the beamlets is calculated from the rms of the fitted Gaussian peaks. Suppose we get three arrays of parameters from multi-Gaussian fits of the projection, a , b and c , which are the intensity, peak position and sigma of the peaks. The slit positions are represented by an array x . The centroid of the beam at the mask is $\langle x \rangle = \frac{1}{\sum_{i=1}^n a_i} \sum_{i=1}^n (a_i * x_i)$, here n is the number of beamlets. The rms size at the mask is

$$\langle x^2 \rangle = \frac{1}{\sum_{i=1}^n a_i} \sum_{i=1}^n (a_i * (x_i - \langle x \rangle)^2)$$

The average divergence of the beamlets is given by $x'_i = (b_i - x_i)/L$. The average divergence of the sampled beam is $\langle x' \rangle = \frac{1}{\sum_{i=1}^n a_i} \sum_{i=1}^n (a_i * x'_i)$. The rms divergence of the beamlets is $\sigma'_i = c_i/L$. The rms divergence of the sampled beam at the mask is

$$\langle x'^2 \rangle = \frac{1}{\sum_{i=1}^n a_i} \sum_{i=1}^n (a_i * \sigma_i'^2 + a_i * (\sigma_i' - \langle x' \rangle)^2)$$

The position angle correlation term is

$$\langle xx' \rangle = \frac{1}{\sum_{i=1}^n a_i} \left(\sum_{i=1}^n a_i * x_i * x'_i - \sum_{i=1}^n a_i \langle x \rangle \langle x' \rangle \right)$$

Then the emittance is calculated by

$$\epsilon = \sqrt{\langle x^2 \rangle \langle x'^2 \rangle - \langle xx' \rangle^2}$$

*The work was performed under Contract No. DE-AC02-98CH10886 with the U.S. Department of Energy.

[†] cliu1@bnl.gov




Figure 2: The intensity distribution of sampled beamlets at the mask

SIMULATION

It turns out to be difficult to implement cylindrically non-symmetrical masks in particle tracking code. Therefore, a standalone Python code has been developed to simulate a beam distribution in phase space and to track the distribution through a drift space. Space charge effects are not considered. The statistical error is minimized by generating and tracking 500,000 particles. The density distribution is set to be Gaussian in 4D phase space with standard deviation of 1 mm for position and 1 $mrad$ for divergence for both planes (numbers are chosen according to the expected BNL ERL beam parameters). In the following, we will try to recover horizontal emittance with the algorithm presented in previous section.

The exact horizontal emittance of initial beam is 1.001 $mm \cdot mrad$. The vertical multi-slit mask is designed with a slit width of 0.1 mm and a spacing between slits of 0.9 mm . One of the slits is set to be centered on the beam. The intensity distribution of the sampled beamlets at the mask is shown in Fig. 2. The horizontal emittance of the sampled beam is 0.998 $mm \cdot mrad$. This shows that the sampled beam represents the real beam well in terms of emittance.

After propagation in a drift space ($L = 0.15 m$), the beamlets project onto a profiler (YAG screen for the BNL ERL) with a 2D image shown in Fig. 3.

The projection of the 2D image at the profiler on the horizontal plane produces a 1D distribution of multiple quasi-Gaussian peaks. A Python program fits the distribution to multiple Gaussian peaks (a good approximation for our case with narrow slits). In the process, one finds the intensity of each beamlet, rms width and peak location. The Gaussian fits of the original distributions are shown in Fig. 4. The calculated emittance is 1.067 $mm \cdot mrad$.

Slit width dependency

The Gaussian peak assumption and calculation of rms divergence of beamlets are possible due to the fact that the slit width is relatively small. Therefore, the finite slit width may introduce a systematic error in the final deter-




Figure 3: The intensity distribution of sampled beamlets at the profiler for a drift length of 0.15 m




Figure 4: The horizontal projection of 2D image on the profiler and its multi-Gaussian fitting for a drift length of 0.15 m

mined beam emittance; in principle, the narrower the slit, the closer the measured and real emittances will be. We studied the slit width dependency of the retrieved beam emittance with results shown in Table 1. In these simulations, the sum of slit width and slit spacing is kept constant at 1 mm so that total number of beamlets is always seven. Real emittance refers to the emittance of the initial beam, the sampled emittance is the emittance of the beam sampled by multi-slit mask, the simulated emittance is the emittance determined by the algorithm introduced. Deviation refers to the relative difference between simulated emittance and sampled emittance.

The slit width correction has been developed and will be presented in a separate note.

Drift length dependency

Slit widths smaller than 80 μm are difficult to produce due to mechanical fabrication limitations. For the BNL ERL, the slit width is designed to be 100 μm . One other

Table 1: Slit width dependency of simulated emittance

Slit Width	Slit Spacing	Drift Length	Real Emittance	Sampled Emittance	Simulated Emittance	Deviation
0.05 mm	0.95 mm	150 mm	1.000 mm · mrad	0.993 mm · mrad	0.996 mm · mrad	0.3 %
0.08 mm	0.92 mm	150 mm	1.000 mm · mrad	0.995 mm · mrad	1.009 mm · mrad	1.4 %
0.10 mm	0.90 mm	150 mm	0.998 mm · mrad	0.991 mm · mrad	1.012 mm · mrad	2.1 %
0.12 mm	0.88 mm	150 mm	1.003 mm · mrad	1.006 mm · mrad	1.037 mm · mrad	3.1 %
0.15 mm	0.85 mm	150 mm	1.001 mm · mrad	0.993 mm · mrad	1.037 mm · mrad	4.4 %

Table 2: Drift length dependency of simulated emittance

Slit Width	Slit Spacing	Drift Length	Real Emittance	Sampled Emittance	Simulated Emittance	Deviation
0.10 mm	0.90 mm	100 mm	1.002 mm · mrad	1.005 mm · mrad	1.043 mm · mrad	3.8 %
0.10 mm	0.90 mm	120 mm	1.003 mm · mrad	0.997 mm · mrad	1.024 mm · mrad	2.7 %
0.10 mm	0.90 mm	150 mm	1.000 mm · mrad	0.997 mm · mrad	1.013 mm · mrad	1.6 %
0.10 mm	0.90 mm	180 mm	0.998 mm · mrad	0.990 mm · mrad	0.998 mm · mrad	0.8 %




Figure 5: The horizontal projection and its multi-Gaussian fitting for drift length 100 mm case




Figure 6: The horizontal projection and its multi-Gaussian fitting for drift length 230 mm case

parameter which has impact on the simulated emittance is the drift length. The well accepted criteria is that the drift length should be long enough until the beamlets overlap. The following study explores the drift length dependency with results shown in Table 2.

The horizontal distribution and its multi-Gaussian fitting for 100 mm and 230 mm drift length are shown in Fig. 5 and 6. The beamlets overlap significantly with each other at a 230 mm drift length. We were able to determine a more accurate emittance from the fitting at 230 mm than at 100 mm. We believe this is due to the fact that the slit width contribution is less when the drift length is longer. Therefore, beamlet overlap is acceptable and desirable as long as reasonable fitting can be produced.

SUMMARY

We developed a program for analyzing a multi-slit image for emittance measurement. The functionality was verified

in simulations. From these we conclude that the narrower the slit width the better precision of the emittance measurement and that beamlets overlap on the profile screen is to some extent desirable. In the future, we will include space charge effects in the simulation.

REFERENCES

- [1] P. Piot, J. Song, R. Li, GA Krafft, D. Kehne, K. Jordan, E. Feldl, and J.C. Denard. A multislit transverse-emittance diagnostic for space-charge-dominated electron beams. In *Particle Accelerator Conference, 1997. Proceedings of the 1997*, volume 2, pages 2204–2206. IEEE, 1997.
- [2] Y. Li-Xin, D. Ying-Chao, X. Dao, L. Ren-Kai, Q. Hou-Jun, H. Wen-Hui, T. Chuan-Xiang, L. Yu-Zheng, and C. Jian-Ping. Multislit-based emittance measurement of electron beam from a photocathode radio-frequency gun. *Chinese Physics Letters*, 25:1640, 2008.
- [3] M. Zhang. Emittance formula for slits and pepper-pot measurement. *Fermilab-TM-1988*, October, 1996.